

13oz Stainless Steel Coffee Cup

SUBLIMATION

Printing	When using SubliJet refer to the Sawgrass Print Manager Manual. If using Epson or another brand of ink, use the instruction manual provided from the vendor you purchased your ink from. All images should be MIRRORED unless specified below.
Important	When the image is printed, it may look dull on the paper—this is normal. Trim the image to make it easier to position on your item. Secure your image to the object with heat tape to keep it from slipping or shifting.
	When pressing is done, Open the press slowly and gently remove the object and remove the paper (be careful not to let the paper shift across the surface of the object, or you may create a "ghost" image).
Heat Press Setup	Before pressing, test the pressure using a blank coffee cup. The pressure should be light . Adjust pressure accordingly. Ensure that your mug press has reached the idle or press temperature before using.
	Do not use excessive pressure. Doing so will damage your mug press and damage your item.
Special Notes	Please remove the plastic lid before placing it in a mug press.
Pressing	OVERVIEW Press Temperature: 350°F for 60 seconds (1 min) Light Pressure, hot peel
	 Recommended Printable area when using a mug press: Approx. W7.5" x H3.5". 1. Tape imaged sublimation paper onto your enamel mug. Place image facing the mug. Leave a 0.5" margin between the top and the top of your image. 2. Set the mug press at 375°F for 60 seconds. If your press has an idle and press temperature setting, adjust the time accordingly.
	 Ensure mug press has reached temperature. Place the mug into your mug press. Close Mug Press.
	 Close Mug Press. Once pressing is done, open mug press, and take cup out of press. Use gloves or heat resistant cloth to handle the hot cup. Peel sublimation paper off.
	7. Leave on table to cool. You can dunk in water for faster cooling.
	Caution: Coffee Cup is extremely hot when in the heat press, do not handle with bare hands.
	Note: Temperature and time settings are only a guide/starting point, some mug presses may require some fine tweaking of the temperature and time.

For Technical Support and to Re-Order

Tel: 1-800-565-5686 | Fax: 1-800-565-5622 | www.jotoimagingsupplies.com Blaine WA, Las Vegas NV, Nashville TN, Coquitlam BC, Brampton ON